



The **WISE** Choice

EASTMAN WORLD

Welcome to Eastman World - Your Global Partner in Energy Solutions!



POWER SOLUTION

HOME INVERTERS & UPS | ELECTRICAL ACCESSORIES

Eastman Introduction

Founded in 2006

Established in 2006, Eastman Auto & Power Limited is a well-known name in the field of solar energy, energy storage, and power electronics, boasting a USD 300 million revenue and a dedicated workforce of over 3,000 professionals. Building on the group's decades-long success and maintaining the trust of our partners, Mr. Jagdish Rai Singal ventured into the future of energy with Eastman Auto & Power Limited. Today, the business spans over 25 countries across Asia and Africa, providing the world with cutting-edge products that have set new benchmarks in their respective segments. Driven by innovation, we continually set industry standards, ensuring uninterrupted power supply for residential, commercial, and industrial applications.

Our global solar distribution business provides reliable and high-quality solar solutions, including solar inverters, solar panels, solar batteries (tubular, carbon, gel and lithium) solar pump inverters, solar charge controllers, and more. Our products offer a range of solutions to help you make the switch to clean energy. With us as your unwavering partners, we forge a sustainable future, amplifying global excellence through transformative products and services.





SINE WAVE - HOME INVERTER

900VA ~ 5500VA

Introduction

Our Sine Wave Home Inverter is the perfect solution to ensure your home stays powered up efficiently and seamlessly. Designed to provide clean and stable power, it ensures the smooth functioning of all your devices, from sensitive electronics to essential appliances.

Product Features

- Unity power factor VA=WATT (*Bulb load)
- Peak load peak output (PLPO)
- Start & Run compressor load/motor load as per rating
- Full load output voltage highest among its peers @ nominal battery voltage
- Zero Volt pick up
- Start & Run SMPS load (LED Lights) as per rating

Product Specifications

MODEL NAME	SINO 900VA	SINO 1200VA	SINO 1800VA	SINO 2500VA	SINO 4000VA	SINO 5500VA
Voltage	12V		24V		48V	
UPS BACKUP MODE TESTING						
Power Rating	900W	1200W	1800W	2500W	4000W	5500W
Power Factor	Unity					
No Load O/P Voltage	225V±10V					
Full Load O/P Voltage (Till Low Battery Alarm)	180V-210±10V		190V-210±10V			
No Load Battery Current	<2.5 AMP					
Full Load Battery Current	75±3A	100±3A	75±3A	105±3A	83±3A	110±3A
Over Load Battery Current	83A±3A	110A±3A	79A±3A	115A±3A	93±3A	120A±3A
Inverter Efficiency @ Nominal Battery Voltage	>75%		>80%	>75%	>80%	>80%
O/P Frequency (No Load & Full Load)	50Hz ± 0.5Hz					
Low Battery Indication Voltage (Std Mode) @ Battery Terminal	10.7±0.25V		21.4V±0.5V		43.6V±1V	
Low Battery Shutdown Voltage (Std Mode) @ Battery Terminal	10.5±0.25V		21V±0.5V		42.8V±1V	
Low Battery Indication Voltage (High Mode) @ Battery Terminal	10.9±0.25V		21.8V±0.5V		43.6V±1V	
Low Battery Shutdown Voltage (High Mode) @ Battery Terminal	10.7±0.25V		21.4V±0.5V		42.8V±1V	
No Load & Full Load O/P Short Ckt Protection	Available					
Output Waveform	Pure Sine Wave					
Over Load Shut Down Protection	Available					
Over Temperature Protection	87°C ± 10°C			100°C ± 10°C		
Over Temperature Recovery	77.7°C ± 10°			90°C ± 10°		
Re-Tries During Battery Low Cut Off (Narrow Mode)	No Reset			No Reset		
Re-Tries During Battery Low Cut Off (Wide Mode)	No Reset			No Reset		
Manual Reset During Battery Low (Using On/Off Switch)	Power On/OFF switch available			Power On/OFF switch available (for 3 times)		
Re-Tries During Over Load (Narrow Mode)	No Reset					
Re-Tries During Over Load (Wide Mode)	Auto 5 Times					
Re-Tries During O/P Short Circuit Test	No Reset					

Product Specifications

MAINS MODE						
Mains Low Cut (Narrow Mode)	180V± 10V					
Low Cut Recovery (Narrow Mode)	190V± 10V					
Mains High Cut (Narrow Mode)	265V± 5V					
High Cut Recovery (Narrow Mode)	255V± 10V					
Mains Low Cut (Wide Mode)	90V± 10V		110V± 10V			
Low Cut Recovery (Wide Mode)	100V± 10V		120V± 10V			
Mains High Cut (Wide Mode)	300V± 10V		280V± 10V			
High Cut Recovery (Wide Mode)	285V± 10V		270V± 10V			
Battery Charging Boost Voltage High Mode @ 220Vac	14.5V± 0.25V		29V± 0.5V		58V± 1V	
Battery Charging Float Voltage High Mode @ 220Vac	13.8V± 0.25V	13.8V± 0.25V	27.6V± 0.5V		55.2V± 1V	
Battery Charging Boost Voltage Std Mode @ 220Vac	14.2V± 0.25V	14.2V± 0.25V	28.4V± 0.5V		56.8V± 1V	
Battery Charging Float Voltage Std Mode @ 220Vac	13.6V± 0.25V		27.2V± 0.5V		54.4V± 1V	
Battery Charging Current @ 220Vavc (Std Mode)	16A ± 2A					
Battery Charging Current @ 220Vavc (High Mode)	18A ± 2A					
Circuit Breaker trip @ Mains Mode	Available					
Changeover From Mains To Backup (Ups Mode @ 200W Bulb Load)	<15ms	–	–	–	–	–
Changeover From Mains To Backup (Std Mode @ 200W Bulb Load)	<15ms	–	–	–	–	–
Changeover From Backup To Mains (Ups Mode @ 200W Bulb Load)	<15ms	–	–	–	–	–
Changeover From Backup To Mains (Std Mode @ 200W Bulb Load)	<15ms	–		–	–	–
Changeover From Mains To Backup (Ups Mode @ 400W Bulb Load)	–	<15ms		–	–	
Changeover From Mains To Backup (Std Mode @ 400W Bulb Load)	–	<15ms		–	–	
Changeover From Backup To Mains (Ups Mode @ 400W Bulb Load)	–	<15ms		–	–	
Changeover From Backup To Mains (Std Mode @ 400W Bulb Load)	–	<15ms		–	–	
Changeover From Mains To Backup (Ups Mode @ 800W Bulb Load)	–	–		<15ms	<15ms	
Changeover From Mains To Backup (Std Mode @ 800W Bulb Load)	–	–	–	<15ms	<15ms	
Changeover From Backup To Mains (Ups Mode @ 800W Bulb Load)	–	–	–	<15ms	<15ms	
Changeover From Backup To Mains (Std Mode @ 800W Bulb Load)	–	–	–	<15ms	<15ms	
PROTECTIONS						
Input Overload	Circuit Breaker			MCB		
Output Short Ckt	Electronic Current Limiting					
Battery Short Ckt	Fuse					
Output Over Load (Std Mode)	Complete Shut Down After 5 Reset					
Battery High Protection	15.5V±1V		31V±1V		62V±1V	
Air Condition Load Capacity	N/A	N/A	N/A	1 Ton Ac	2 Ton Ac	2 Ton Ac
Drain To Drain Short Ckt	Available					
Bulb Load Testing Criteria	Keep The System In Mains Mode @250V, Bulb Load Is 900W	Keep The System In Mains Mode @250V, Bulb Load Is 1800W	Keep The System In Mains Mode @250V, Bulb Load Is 1800W	Keep The System In Mains Mode @250V, Bulb Load Is 2500W	Keep The System In Mains Mode @250V, Bulb Load Is 4000W	Keep The System In Mains Mode @250V, Bulb Load Is 5500W
Weight	10.3 Kgs	11.67 Kgs	18.2 Kgs	27.6 Kgs	36.4 Kgs	39.9 Kgs
Display	LCM			LCD		

Product Specifications

VISUAL INDICATION		
Battery Voltage	Shows Battery Voltage	
Input Voltage	Shows Input Voltage	
Backup Mode	Battery Symbol, Battery Graph , Battery Voltage, Selected Mode (Narrow Or Wide)	UPS on, O/P voltage, battery voltage, O/P frequency, load %
Mains Mode	Mains Plug Symbol, Battery Graph , Input Voltage, Battery Voltage, Selected Mode (Narrow Or Wide)	AC Input Voltage, I/P Frequency, Battery Voltage, Battery Charging Condition,
Narrow/Wide Mode	Narrow & Wide Symbol	–
Short Circuit	Warning Symbol,Over Load Symbol Continue , Sct, Battery Symbol, Battery Graph, Selected Mode (Narrow Or Wide)	UPS Off short circuit
Over Load Alarm	Over Load Symbol , Warning Symbol, Battery Symbol, Battery Graph, Battery Voltage, Selected Mode (Narrow Or Wide)	Overload , Load % , Pls Reduce load
Over Load Shut Down	Over Load Symbol , Warning Symbol,Ovl, Battery Symbol, Battery Graph, Selectd Mode (Narrow Or Wide)	UPS Off Overload
Ckt Breaker Trip	Warning Symbol,Ckt Breaker Symbol , Cbt Battery Graph, Selected Mode (Narrow Or Wide)	MCB Trip, Pls RESET, Select Bypass
Low Battery Alarm	Battery Graph Blinks, Warning Symbol, Battery Voltage, Battery Symbol, Selected Mode (Narrow Or Wide)	Low Battery, Battery Voltage, Pls Reduce load
Low Battery Shut Down	Battery Symbol, Battery Graph, Warning Symbol, Lob, Selected Mode (Narrow Or Wide)	UPS Off, Low battery
Over Temperature Shut Down	Over Temperature Symbol , Warning Symbol , Otp, Battery Symbol, Battery Graph, Selected Mode (Narrow Or Wide)	Under Protection Over Temprature
Buzzer Mute Option	Switch Off The On/Off Switch And Then Buzzer Mute Symbol Continue Glow	Switch Off The On/Off Switch
Front Switch Off	Off, Selected Mode (Narrow Or Wide) , Buzzer Mute Symbol	AC Output Range, UPS Off
Welcome message	–	Shows Eastman welcomes you with model name
AUDIO INDICATION		
Over Load Occurs	Beep With Delay	
Over Load Shut Down	No Beep	
Low Battery Occurs	Beep With Delay	
Low Battery Shut Down	No Beep	
Over Temperature Shut Down	Continuous Beep	
Short Circuit	Continuous Beep	
Circuit Breaker trip	Continuous Beep	
Buzzer Mute Option	Buzzer Can Be Muted Any Time During Any Audio Indication By Pressing On/Off Switch	





www.eastmanworld.com
marketing@eastmanworld.com

AMPS MIDDLE EAST FZ LLC

#703, 7TH Floor, Deira Twin Tower,
Baniyas Square, Deira, Dubai (UAE)

EASTMAN AUTO & POWER LTD.

ASF Towers, 249, Udyog Vihar Phase-4, Gurugram,
Haryana-122016, India

GUANGDONG EASTMAN NEW ENERGY CO., LTD

#1602, Meilan business centre, Intersection of Xixiang Avenue
and Qianjin Second Road, Bao'an, District, Shenzhen-518102, China

Follow us on »  @eastman_world  @EastmanWorld  @EastmanWorld